

INSTALLATION  
INSTRUCTIONS

FIXTURE TYPE \_\_\_\_\_

SC/P6 PENDANT ASSY  
P-I/P-ID-33,33JR,36,36JR,  
37,37JR,P-D-38S,38M,38L  
PG. 1 OF 1

P/C 510400-3000

DO NOT MODIFY OR ALTER THIS PRODUCT IN ANY WAY, OR INSTALL IN ANY FASHION WHICH IS CONTRARY TO THE INSTRUCTIONS CONTAINED HEREIN. IF YOU HAVE ANY QUESTIONS REGARDING THIS PRODUCT OR THE INSTALLATION OF IT, PLEASE CALL LITECONTROL ENGINEERING AT 781-294-0100.

GENERAL NOTES:

1. Pendant is made to install directly over 3-1/2" x 2-1/8" deep octagonal outlet box, 2 1/8" x 4" handy box or a 2 1/8" x 3" switch box with plaster ring. (supplied by contractor).  
Outlet boxes must be mounted flush to ceiling.  
WARNING: The National Electrical Code requires that any fixture weighing more than (50) pounds be independently supported of an outlet box.
2. These pendants are to be used only in conjunction with LITECONTROL products for which they were furnished. DO NOT use them for support of any other items or in any fashion which is contrary to this instruction sheet.

INSTRUCTIONS:

1. This instruction sheet is used with Fixture Installation sheets No. 510357,510359,510421,510422,510425,510426,510427,510428, 510431,510432,510433,510434 or 510579.
2. Cut a piece of feed cord (shipped separately) equal to the distance from ceiling to top of fixture and add 24".
3. Insert one end of feed cord into outlet box and make wiring connections.
4. Slide Swivel Ball onto coupled end of stem and insert stem thru center hole in Canopy Support strap. Insert feed cord thru stem and mount Support strap to outlet box with outlet box screws.
4. Slide Canopy onto stem and align plastic tree clips with (2) holes in support strap. Push canopy up until clips engage and canopy is flush against ceiling.
5. Slide Thread cover onto stem and thread a locknut onto bottom thread of stem. Slide the Cable Retaining plate over feed cord and then attach to bottom of stem with threaded coupling. Tighten locknut against top of retaining plate and slide thread cover down against locknut.
6. Refer to Fixture installation sheet for mounting fixture to cables.

